

MAX BR2 Pro



Quick Look

| | | | | | |
|----------|--------------|--------------|-------------------|-----------------------------------|---------------------------------|
| Cellular | Ethernet WAN | Ethernet LAN | Router Throughput | PepVPN Throughput (No Encryption) | PepVPN Throughput (256-bit AES) |
| 2 | 2 (2.5G) | 4 (GE) | 1Gbps | 400Mbps | 200Mbps |

Interfaces

| | |
|----------------|-----|
| Serial (RS232) | Yes |
| Wi-Fi AP | Yes |
| Wi-Fi WAN | Yes |
| USB WAN | Yes |
| GPIO | Yes |

Performance

| | |
|--------------------------------------|-------|
| Recommended Users | 1-150 |
| Number of PepVPN / SpeedFusion Peers | 2/5^ |

Wireless Details

| | |
|---------------------------------------|-------------------------------------|
| LTE Category Options | 2x 5G 2x CAT20 |
| Band 71 | Yes |
| SIM Slots | 4 |
| Wi-Fi Radio | Dual (2.4GHz + 5GHz) 2x2 Wi-Fi 6 |
| SIM Card Size | Nano-SIM (4FF) |
| Transmit Power (2.4GHz, single chain) | 21dBm |
| Transmit Power (5GHz, single chain) | 22dBm |
| Multiple SSIDs | 16 |
| Captive Portal | Yes |
| GPS | Yes |

Features

| | |
|-----------------------------------|------|
| Ignition Sensing | Yes |
| Remote SIM (used in SIM Injector) | Yes |
| 802.1 q VLANs Supported | 16 |
| Drop-In Mode | Yes |
| High Availability | Yes |
| Ip Passthrough | Yes |
| WAN as LAN | Yes |
| Web Blocking | Yes |
| Web Filtering Blacklist | Lite |
| In Control Cloud Management | Yes |
| GPS Fleet Management | Yes |

VPN Functionality

| | |
|----------------------------------|-------|
| PepVPN | Yes |
| SpeedFusion Hot Failover | Yes |
| SpeedFusion WAN Smoothing | Yes |
| SpeedFusion Bandwidth Bonding | Yes * |
| Number of IPsec Tunnels | 5 |
| Maximum PPTP/L2TP/ OpenVPN Users | 3 |

[+] The WAN port can act as a LAN port if needed.

[^] 2 PepVPN Peers are enabled by default. 5 PepVPN Peers are enabled with PrimeCare Subscription, complimentary for the first year

[*] Requires PrimeCare Subscription, complimentary for the first year

[1] The frequency range for 2.4GHz and 5GHz are 2412–2472 MHz and 5180–5825 MHz respectively.

[2] Recommended user: Recommendation for sizing purposes only. No software restrictions applied.

[3] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP. x

[4] Transmit power can be configured on the Web Admin Interface.

[5] Cache Throughput refers to the speed of routing content from disk drive to LAN.

Hardware

| | |
|--|-----------------------------|
| Enclosure | Indoor, Metal |
| Terminal Block Power Connector for Mobile/Vehicular Deployment | No |
| AC Adapter | No |
| Input Voltage | DC 10 - 30V |
| PoE Input | 802.3at PoE |
| PoE Output | No |
| Power Consumption | Max: 30W |
| Dimensions in inches | 8.58 x 7.68 x 1.61 inches |
| Dimensions in mm | 218 x 195 x 29.5 mm |
| Weight (Pound) | 2.42 pounds |
| Weight (Grams) | 1.1 kg |
| Operating Temperature | -40°– 149° F -40°– 65° C |
| Humidity | 15% – 95% (non-condensing) |

Certifications

| | |
|--|-------------------------|
| FCC, CE, RoHS | In Progress |
| E-Mark (Motor Vehicle) | In Progress |
| EN 61373 Shock and Vibration Resistance | In Progress |
| EN 50155 Railway Applications – Electronic Equipment used on Rolling Stock | In Progress |
| EN 61000 Electromagnetic Compatibility | In Progress |
| Warranty | 1-Year Limited Warranty |