



## Built to last

Sturdy industrial-strength designed for continuous high-traffic operation.



## Stay Connected

With two SIM slots and an eSIM, the MAX Adapter always has a way to connect.

## Compatible with 5G

MAX Adapter now offers a 5G compatible device option. Bringing 5G connectivity to your devices.



Peplink Certified Reseller

Tel: (813) 751-2039 | <https://accesswds.com>

**MAX ADAPTER**  
State-of-the-art Cellular Modem at a breakthrough price point



## Portable

The light and sleek enclosure offers portability in the palm of your hands.





## Specifications

<b>Cellular WAN Interfaces</b>	Single 5G Modem	<b>Operating Temperature</b>	32° – 104°F / 0° – 40°C
<b>Redundant SIM Slot</b>	Yes	<b>Humidity</b>	15% – 95% (non-condensing)
<b>Downlink/Uplink Datarate</b>	5G: 4 Gbps / 700 Mbps LTE CAT-20: 2 Gbps / 150 Mbps	<b>Warranty</b>	1-Year Limited Warranty
<b>Antenna Connectors</b>	4x SMA Cellular	<b>Certifications</b>	FCC, CE, IC
<b>Power Input</b>	5V USB-C	<b>Package Content</b>	MAX Adapter 5G, 4x LTE/5G LTE Antennas (ACW-235), USB-C Female to USB-A Male Adapter, USB-C Power Cable
<b>Power Consumption</b>	5W (nominal), 8W (max.)	<b>US Carrier Certifications</b>	AT&T, T-Mobile, US Cellular
<b>Dimensions</b>	3.9 x 2.8 x 0.6 inches / 100 x 71 x 15 mm		
<b>Weight</b>	120g		

## Ordering information

Product Code	Carrier / Category	5G Bands	LTE Bands
MAX-ADP-5GH-T	Global / 5G	<b>5G (NSA) Sub 6Ghz:</b> n1, n2, n3, n5, n28, n41, n66, n71, n77, n78, n79	B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71



Peplink Certified Reseller  
Tel: (813) 751-2039 | <https://accesswds.com>



## Specifications

<b>Cellular WAN Interfaces</b>	Single LTE Modem	<b>Weight</b>	120g
<b>Redundant SIM Slot</b>	Yes	<b>Operating Temperature</b>	32° – 104°F / 0° – 40°C
<b>Downlink/Uplink Datarate</b>	CAT-12: 600 Mbps / 150 Mbps CAT-6: 300Mbps / 50Mbps	<b>Humidity</b>	15% – 95% (non-condensing)
<b>Antenna Connectors</b>	2x SMA Cellular, 1x SMA GPS	<b>Warranty</b>	1-Year Limited Warranty
<b>Power Input</b>	5V USB-C	<b>Certifications</b>	FCC, CE, IC
<b>Power Consumption</b>	5W (nominal), 8W (max.)	<b>Package Content</b>	MAX Adapter, 2x LTE Antennas (ACW-813), USB-C Female to USB-A Male Adapter, USB-C Power Cable
<b>Dimensions</b>	3.9 x 2.8 x 0.6 inches / 100 x 71 x 15 mm	<b>US Carrier Certifications</b>	Verizon, AT&T

## Ordering information

Product Code	Carrier / Category	LTE Bands	3G Bands
MAX-ADP-LTEA-K-T	Global CAT-12	B1, B2, B3, B4, B5, B7, B8, B9, B12, B13, B18, B19, B20, B26, B28, B29, B30, B32, B41, B42, B43, B46, B48, B66	HSPA+: B1, B2, B4, B5, B6, B8, B9, B19
MAX-ADP-LTEA-R-T	America CAT-12	B1, B2, B3, B4, B5, B7, B8, B9, B12, B13, B14, B18, B19, B20, B26, B29, B30, B32, B41, B42, B43, B46, B48, B66	HSPA+: B1, B2, B4, B5, B6, B8, B9, B19
MAX-ADP-LTEA-W-T	Global CAT-6	B1, B2, B3, B4, B5, B7, B8, B12, B13, B20, B25, B26, B29, B30, B41	WCDMA/HSPA+/DC-HSPA+: B1, B2, B3, B4, B5, B8

## Accessories

Product Code	Description
ACW-232	GPS Antenna



Peplink Certified Reseller  
Tel: (813) 751-2039 | <https://accesswds.com>